

# Nokia ONT U-010X-B Quick Reference Guide

## 1. Product Overview

The Nokia Optical Network Terminal (ONT) U-010X-B is designed to cater to residential customer requirements and offers data services to the subscriber through fiber to the home (FTTH) or fiber to the premises (FTTP) applications. This device terminates either a 10G symmetrical Passive Optical Network (XGS-PON) or a Gigabit Passive Optical Network (GPON) interface, both compliant with a Full Service Access Network (FSAN). This ONT is compliant with ITU-T G.9807.1, G.984, G.988 and can be managed from a remote site.



Figure 1 Nokia ONT U-010X-B front view



Figure 2 Nokia ONT U-010X-B back view

## A. Technical Specifications

Height: 30 mm (1.19 in)

Width: 135 mm (5.31 in)

Length: 135 mm (5.31 in)

Weight: 0.28 Kg (0.62 lb)

Desktop or wall mount

### Power consumption:

- Standby mode: 5.1 W
- Typical mode: 6.6 W

© 2026 Nokia. Nokia Confidential Information. Use subject to agreed restrictions on disclosure and use.

If you have received this document in error, do not use or copy this document for any purpose nor disclose its contents to any other person.

## B. Manufacturer Information

### For Products Purchased in EU/EAA Countries

The products are manufactured and imported by Nokia Solutions and Networks Oy, Karakaari 7, 02160 Espoo, Finland.

Nokia is a registered trademark of Nokia Corporation.

Please contact your Internet Services Provider in case of questions on the product.

## 2. Safety Guidelines

ALWAYS READ THE PRODUCT GUIDE BEFORE SET UP OR USE OF THE PRODUCT. IT IS YOUR RESPONSIBILITY TO FAMILIARIZE YOURSELF WITH THE PRODUCT GUIDE AND WARNINGS, AND TO USE A PRODUCT PROPERLY. CONTACT YOUR INTERNET SERVICES PROVIDER FOR FURTHER QUESTIONS.

### Warning - Risk of electric shock or fire

Connect the Product power adaptor or cord to the right supply voltage (for example, 230V in Europe, Australia, South Africa and 120V in US).

The socket-outlet shall be easily accessible.

Pay attention to the power load of the electrical outlet and possible extension cord. An overburdened power outlet or damaged cords and plugs may cause electric shock or fire. Check the power cords regularly. If you find any damage, replace the cord immediately.

Do not connect the plug into an extension cord, receptacle, or other outlet unless the plug can be fully inserted with no part of the blades exposed.

Leave adequate space for heat dissipation to avoid any damage caused by overheating the Product. Do not cover the Product or its ventilation holes. Blocking the ventilation holes may cause fire.

Use the power adapter provided with your Product and do not fasten the power cable to building surfaces. Ensure the cable can move freely. Do not place heavy objects on the cable.

Do not use the Product outside, and make sure all the connections are indoors.

Do not install, use, or service this Product during a thunderstorm. There is a remote risk of electric shock from lightning.

### Caution - Potential equipment damage

Follow these recommendations to protect yourself and the Product from harm:

- Do not look directly at the optical port without protection.
- Do not insert any sharp object into the openings of a Product.
- Do not put the Product near a heat source. Avoid placing the Product in direct sunlight.
- Do not put the Product in damp or wet locations; for example, near a bathtub, washbowl, kitchen sink or laundry tub, in a wet basement, or near a swimming pool. Do not spill any liquid on the Product.
- Do not touch the Product or its power adapter or cord with wet hands.
- Do not place the Product on an unstable surface or support.
- Do not place heavy objects on top of the Products.
- Do not use liquid or aerosol cleaners; unplug the Product and use a soft, dry cloth for cleaning.
- When connecting a PC or other electronic device to a Product, make sure you use the right cables and connect the device to the right port of the Product. Incorrect connections may damage the device and/or the Product.
- Do not open or try to open the Product. Opening or removing covers can expose you to dangerous high voltage points or other risks.

It is recommended that users and other individuals maintain a distance of at least 10 cm between themselves and the Product to avoid exposure. The Product contains components that emit an electromagnetic field and could interfere with pacemakers or other electronic medical devices. If you have a pacemaker or other implantable or personal medical device, please consult your physician or medical device manufacturer about the required minimum safe distance between the Product and your medical device.

Keep your product and accessories out of reach of pets. They could damage it and cause injury or electrocution.

If the Product malfunctions or fails to perform as expected, stop using it immediately.

The product is expected to operate at a temperature of -5 to 45 degrees Celsius (23°F to 113°F) for a relative humidity between 5% and 95%.

## 3. Install the ONT

The ONT is normally installed by a professional installer.

© 2026 Nokia. Nokia Confidential Information. Use subject to agreed restrictions on disclosure and use.

If you have received this document in error, do not use or copy this document for any purpose nor disclose its contents to any other person.

# Nokia ONT U-010X-B Quick Reference Guide

1. Plug the power cable to the ONT into power input jack.
2. Plug the power socket to the wall socket.
3. Remove the protective cap on the optical port of the ONT.
4. Remove the protective cap from the optical fiber.
5. Plug the optical fiber to the optical port of the ONT.
6. Connect the ONT to the home router via an Ethernet cable into the Ethernet port.
7. Push the power button to be "ON". ("ON" = recessed stated, "OFF" = non-recessed state)

## 4. LED description

The following table describes the LEDs of the device:

LED indicator	LED color and behavior	LED behavior description
POWER	Red solid	Failed on startup (for example corrupt flash), or self-test failed on startup, or self-test failed during regular operation.
POWER	Green flashing	New firmware is downloading.
POWER	Green solid	Normal Power is provided and ONT is not in suspended state of operation to conserve battery (for example, ONT is not in watchful sleep mode).
POWER	Off	No power or ONT is in suspended state of operation to conserve battery (for example, ONT is in watchful sleep mode).
PON (Green -GPON/Blue -XGS-GPON)	Green/Blue solid (Up)	Full communication between OLT and ONT (O5 with OMCI messages downloaded).
PON (Green -GPON/Blue -XGS-GPON)	Green/Blue blinking (fast flashing) (Ranging)	ONT is attempting to range with OLT (O2-O4, O6 (not O5)). Flashing at 2Hz with a 50% duty cycle.
PON (Green -GPON/Blue -XGS-GPON)	Green/Blue blinking (slow flashing) (Ranging)	PON mode is in O1. Flashing at 0.5 Hz with a 50% duty cycle.
PON (Green -GPON/Blue -XGS-GPON)	Red solid (disabled)	O7 and Rogue state triggers this.
PON (Green -GPON/Blue -XGS-GPON)	Red blinking (Not configured)	No full communication between OLT and ONT (O5 without OMCI messages downloaded).
Alarm (for generic variants)	Red flashing	Downstream optical input power is low (close to sensitivity level).
Alarm (for generic variants)	Red solid (on)	Negative indication that the downstream wavelength optical input power is not within the operating range.
Alarm (for generic variants)	Off	Positive indication that the downstream wavelength optical input power is within operating range.
Data	Green flashing	Data activity on 100M/1G. Slow blink: 100M. Fast blink: 1G.
Data	Green solid (on)	100M/1G linkup mode is on.
Data	Yellow solid (on)	2.5 Gbps linkup mode is on.
Data	Yellow flashing	Data activity on 2.5 Gbps.
Data	White solid (on)	5 Gbps linkup mode is on.

© 2026 Nokia. Nokia Confidential Information. Use subject to agreed restrictions on disclosure and use.

If you have received this document in error, do not use or copy this document for any purpose nor disclose its contents to any other person.

LED indicator	LED color and behavior	LED behavior description
Data	White flashing	Data activity on 5 Gbps.
Data	Blue solid (on)	10 Gbps linkup mode is on.
Data	Blue flashing	Data activity on 10 Gbps.
Data	Off	Power off or Ethernet not connected (or no cable, or no powered device connected to the LAN port).

## 5. Accessibility features

### WebGUI compliance with accessibility guidelines

The Device's WebGUI is designed to be accessible for users with disabilities and is compatible with assistive technology.

- Screen reader support: The interface is optimized for screen readers. All menus and settings comply with WCAG 2.1 Level AA.
- Keyboard navigation: You can navigate the full interface using only a keyboard (Tab and Arrow keys) without needing a mouse.

### Tactile indicators

The device features tactile indicators on the panel to help identify interfaces by touch.

- Uplink port: Identified by one tactile dot.
- Setup QR code: A tactile bar is located close to the QR code label, allowing you to locate it for scanning with the Nokia WiFi Mobile App. The exact location of those tactile indicators is described in the Figure 2 Nokia ONT U-010X-B back view.

## 6. EU Declaration of Conformity

Hereby, Nokia Solutions and Networks Oy declares that the Product is in compliance with Low Voltage Directive 2014/35/EU; EMC Directive 2014/30/EU, Directive RoHS 2011/65/EU and 2015/863/EU, Directive Eco-design 2009/125/EC, and European Accessibility Act Directive 2019/882/EU. The full text of the EU declaration of conformity, as well as additional compliance information, is available at [www.nokia.com/notices/declaration-of-conformity/](http://www.nokia.com/notices/declaration-of-conformity/).

Products are for indoor use only.

### Specific precautions for EMC Warning

The Products are compliant with Class B of EN 55032. In a residential environment, this equipment may cause radio interference. The Products are tested to the requirements of EN 55032 (Emissions) and EN 55035 (immunity). There are no specific precautions which must be taken in order to comply with the requirements of Directive 2014/30/EU Essential Requirements in Section 1 of Annex I. In addition, the Products are further tested to ensure spurious emissions are within the specified limits, as well as meeting the requirements for adaptivity, which mitigates against problems caused by co-location with other wireless products. The Products are not subject to the requirements in Section 2 of Annex I of Directive 2014/30/EU for fixed installations.

### End of Life Collection and Treatment



In the European Union and European Economic Area, this label indicates that this product should not be disposed of with household waste. It should be deposited in an appropriate facility to enable recovery and recycling.

The Product is marked with this symbol, which is known as the WEEE mark. WEEE stands for Waste Electronics and Electrical Equipment. Electronic products bearing or referencing the WEEE mark shown above, when put on the market within the European Union (EU) and European Economic Area (EEA), shall be collected and treated at the end of their useful life, in compliance with applicable EU and local legislation. They shall not be disposed of as part of unsorted municipal waste. Due to materials that may be contained in the Product, such as heavy metals or batteries, the environment and human health may be negatively impacted as a result of inappropriate disposal.

© 2026 Nokia. Nokia Confidential Information. Use subject to agreed restrictions on disclosure and use.

If you have received this document in error, do not use or copy this document for any purpose nor disclose its contents to any other person.

# Nokia ONT U-010X-B Quick Reference Guide

At the end of their life, the Products are subject to the applicable local legislations that implement the European Directive 2012/19EU on WEEE. There can be different requirements for collection and treatment in different member states of the European Union.

In compliance with legal requirements and contractual agreements, where applicable, Nokia will offer to provide for the collection and treatment of Products bearing the logo above at the end of their useful life, or Products displaced by Nokia equipment offers. The equipment can be disposed at electronic waste collection points or to stores that sell electronics.



For information regarding take-back of equipment by Nokia, or for more information regarding the requirements for recycling/disposal of the Product, contact your service provider. Regulatory compliance information, including EU Declaration of Conformity, can be found at [www.nokia.com/notices/declaration-of-conformity/](http://www.nokia.com/notices/declaration-of-conformity/).

© 2026 Nokia Solutions and Networks Oy

*Nokia is a registered trademark of Nokia Corporation*

© 2026 Nokia. Nokia Confidential Information. Use subject to agreed restrictions on disclosure and use.

If you have received this document in error, do not use or copy this document for any purpose nor disclose its contents to any other person.